




T.				U_f V	I_f A	U_a V	U_g V	I_a mA	S mA/V	R_i Ω	μ V/V	R_k Ω	U_{fik} V	P_a W	
															R_k Ω
6 AS 7-G 6080 6082	int	1	6,3 ± 10%	2,5	$\left\{ \begin{array}{l} 135 \\ 200 \\ -1700 \\ -2300 \end{array} \right.$	$\left\{ \begin{array}{l} 90 \\ 250 \end{array} \right.$	-30	125	7	280	2	250	impulse $\leq 10 \mu\text{sec}$	300	13
	amer	1	6,3 ± 10%	2,5				125	maximum 6 AS 7-G	maximum 6080, 6082					
	amer	1	26,5 ± 10%	0,6				125	maximum 6080, 6082	maximum 6080, 6082					
6 H 13 C	CCCP	1	6,3 ± 10%	2,8	$\left\{ \begin{array}{l} 90 \\ 250 \end{array} \right.$	$\left\{ \begin{array}{l} -30 \\ -10,5 \end{array} \right.$	80 ± 32 130	5 ± 1,5	460	2,3	$\left\{ \begin{array}{l} 250 \\ 350 \end{array} \right.$	$\left\{ \begin{array}{l} 300 \\ 300 \end{array} \right.$	13		
5998	amer	1	6,3	2,4	110	-10,5	100	15,5	350	5,3		300	13		

T.	$C_{g/k}$ pF	$C_{a/k}$ pF	$C_{g/a}$ pF	C_{fik} pF	$C_{g/g}$ pF	$C_{o/a}$ pF
6 AS 7-G	6,8	2,3	10,5	11	0,7	1,65
6 H 5 C	9,5	5	9,5			
6 H 13 C	7	4,2	9			
6080	6	2,2	8	12,5	0,5	2
6082	6	2,2	8	13	0,5	2

Equivalents

A 1834	Marc = 6 AS 7-G	RK 6080	Ray = 6080	6 H 5 C	CCCP = 6 AS 7-G
A 4475	amer = 6 AS 7-G	6 AS 7-GA	amer = 6 AS 7-G	6 H 11	CCCP = 6 AS 7-G
E 6080	SFR = 6080	6 AS 7-W ¹⁾	amer = 6 AS 7-G	6080-WA ¹⁾	amer = 6080
ECC 230	MuI = 6080				

¹⁾ vide * 4, a, b, g

