

VALVE ELECTRONIC

CV2301

GENERAL POST OFFICE: E-IN-C (S)

Specification: GPO/CV 2301 Issue 1.	<u>SECURITY</u>
Dated: April, 1954.	<u>Specification</u> <u>Valve</u>
To be read in conjunction with K 1001	UNCLASSIFIED UNCLASSIFIED

—> Indicates a change

<u>TYPE OF VALVE</u> - Cathode Ray Tube	<u>MARKING</u>
<u>TYPE OF DEFLECTION</u> - Electrostatic, suitable for symmetric or asymmetric deflection.	See K 1001/4
<u>BULB</u> - Internally coated with conductive coating.	<u>BASE</u>
<u>SCREEN</u> - Y7	B12D
<u>PROTOTYPE</u> - E4412/C/9	

<u>RATING</u>			Note	<u>CONNECTIONS</u>	
				Pin	Electrode
Heater Voltage	(V)	4			G
Heater Current	(A)	1			C
Max. Final Anode Voltage	(kV)	5		1	H
"X" plate Sensitivity	(mm/V)	357/Va3		2	H
"Y" plate Sensitivity	(mm/V)	780/Va3		3	A1
<u>TYPICAL OPERATING CONDITIONS</u>				4	A2
Final Anode Voltage	(kV)	3.0		5	Int. Coating (note D)
Second Anode Voltage	(V)	450		6	
First Anode Voltage	(kV)	2.0		7	Y ₂
				8	X ₂
				9	A ₃
				10	X ₁
				11	Y ₁
				12	
				<u>DIMENSIONS</u>	
				See Drawing on Page 4	

NOTES

- The tube shall be adequately free from microphony.
- When viewing the screen with the tube positioned such that the base spigot is uppermost, a positive voltage applied to the terminal X₁ shall deflect the spot to the left and a positive voltage applied to the terminal Y₁ shall deflect the spot upwards.
- The internal conductive coating shall be of such dimensions that it functions effectively but does not obscure the required useful screen area.
- The tube will normally be operated with A₃ and conductive coating tied, and if a manufacturer so desires, these electrodes may be strapped internally, with the connection omitted from contact marked - "internal conductive coating".

CV2301

TESTS

To be performed in addition to those applicable in K 1001

Test Conditions						Test	Limits		No. Tested	Note
							Min.	Max.		
Deflection Voltages shall be applied asymmetrically in all cases.						<u>CAPACITANCES</u> (pF) 1. Each X or Y plate to all other electrodes. 2. Grid to all other electrodes. 3. One X to one Y plate.	-	25	5%	
a	See K 1001/5A.13.						-	25	(10)	
b	Cathode 80V positive to heater					I _{h-c} (μA)	-	100	100%	
c	V _h	V _{a3}	V _{a2}	V _{a1}	V _g	I _h (A)	0.8	1.3	100%	
	4	0	0	0	0					
d	4	3000	Adjust for optimum focus	2000	Adjust to cut-off	V _g (V)	-40	-80	100%	
e	4	3000	ditto	2000	Adjust	(1) V _g (V)	-1	-	100%	
						(2) Change in value of V _g from test (d) (V)	-	25	100%	
f	4	3000	ditto	2000	ditto	(1) Line width (mm)	-	0.8	100%	
						(2) V _{a2} (V)	400	600	100%	
<u>DEFLECTION</u> - With a sine-wave time base of 10 Kc/s nom. and line length of 70 mm. in the X and Y directions successively, the line width to be measured at the centre of the trace. <u>GRID</u> - The grid will be pulsed positively from cut-off with amplitude equal to the value obtained in test e.(2), the nominal values of pulse duration and recurrence being 100 μ secs. and 100 c/s respectively.										
g	4	3000	ditto	2000	-30	<u>GRID INSULATION</u>				
						(1) Leakage current (μA)	-	5	100%	
Recommended method - See K 1001/5A 3.2 Resistor = 10 megohms.						(2) Increase in voltmeter reading.	-	100%	100%	

TESTS (Continued)

CV2301

Test Conditions						Test	Limits		No. Tested	Note
							Min.	Max.		
h	Vh	Va3	Va2	Va1	Vg	<u>DEFLECTION SENSITIVITIES</u> (1) X-plate (mm/V) (2) Y-plate (mm/V)				
	4	3000	Adjust for optimum focus	2000	Any convenient value		$300/Va3$	$415/Va3$	10%	(10)
j	4	3000	Adjust for optimum focus	2000	Any convenient value	Deviation of spot from centre of screen. (mm)	-	4	100%	
k	4	3000	ditto	2000	ditto	<u>USEFUL SCREEN AREA</u> Diameter (mm)	70	-	100%	
l	4	3000	Adjusted for optimum focus	2000	Any convenient value	<u>TRAPEZOIDAL DISTORTIONS</u> (1) Angles between adjacent sides.	85°	95°	100%	
						(2) Angles between opposite sides.	175°	185°	100%	
m	4	3000	ditto	2000	ditto	(1) Orientation of X axis of deflection relative to 0.0' on drawing. (2) Angles between X and Y axes of deflection.	80°	100°	100%	
n	To be performed in Test Set No. 331.					Afterglow (secs)	5	-	100%	

