



5881

5881

# BEAM POWER TUBE

For audio-frequency power amplifier applications

## GENERAL DATA

### Electrical:


Heater, for Unipotential Cathode:

Voltage . . . . .	6.3	. . . . . ac or dc volts
Current . . . . .	0.9	. . . . . amp

### Mechanical:

Mounting Position . . . . .	Any
Maximum Overall Length . . . . .	3-15/32"
Maximum Seated Length . . . . .	2-29/32"
Maximum Diameter . . . . .	1-7/16"
Bulb . . . . .	T11
Base . . . . .	Short Intermediate-Shell Octal 7-Pin with External Barriers (JETEC No. B7-59)
Basing Designation for BOTTOM VIEW . . . . .	7AC

Pin 1 - No Connection  
 Pin 2 - Heater  
 Pin 3 - Plate  
 Pin 4 - Grid No. 2



Pin 5 - Grid No. 1  
 Pin 7 - Heater  
 Pin 8 - Cathode, Grid No. 3

## AF POWER AMPLIFIER - Class A<sub>1</sub>

### Maximum Ratings, Design-Center Values:

PLATE VOLTAGE . . . . .	400 max.	volts
GRID-No. 2 (SCREEN-GRID) VOLTAGE . . . . .	400 max.	volts
GRID-No. 2 INPUT . . . . .	3 max.	watts
PLATE DISSIPATION . . . . .	23 max.	watts
PEAK HEATER-CATHODE VOLTAGE:		
Heater negative with respect to cathode . . . . .	200 max.	volts
Heater positive with respect to cathode . . . . .	200 max.	volts

### Typical Operation and Characteristics:

Plate Voltage . . . . .	250	300	350	volts
Grid-No. 2 Voltage . . . . .	250	200	250	volts
Grid-No. 1 (Control-Grid) Voltage . . . . .	-14	-12.5	-18	volts
Peak AF Grid-No. 1 Voltage . . . . .	14	12.5	18	volts
Zero-Signal Plate Current . . . . .	75	48	53	ma
Max.-Signal Plate Current . . . . .	80	55	65	ma
Zero-Signal Grid-No. 2 Current . . . . .	4.3	2.5	2.5	ma
Max.-Signal Grid-No. 2 Current . . . . .	7.6	4.7	8.5	ma
Plate Resistance (Approx.) . . . . .	3000	3500	4800	ohms
Transconductance . . . . .	6100	5300	5200	μmhos
Load Resistance . . . . .	2500	4500	4200	ohms
Total Harmonic Distortion . . . . .	10	11	13	%
Max.-Signal Power Output . . . . .	6.7	6.5	11.3	watts



## BEAM POWER TUBE

### Maximum Circuit Values:

Grid-No.1-Circuit Resistance:

For fixed-bias operation . . . . .	0.1 max.	megohm
For cathode-bias operation . . . . .	0.5 max.	megohm

### AF POWER AMPLIFIER - Class A<sub>1</sub>

*Triode Connection - Grid No.2 Connected to Plate*

### Maximum Ratings, Design-Center Values:

PLATE VOLTAGE. . . . .	400 max.	volts
PLATE DISSIPATION. . . . .	26 max.	watts
PEAK HEATER-CATHODE VOLTAGE:		
Heater negative with respect to cathode.	200 max.	volts
Heater positive with respect to cathode.	200 max.	volts

### Typical Operation and Characteristics:

Plate Voltage. . . . .	250	300	volts
Grid-No.1 (Control-Grid) Voltage.	-18	-20	volts
Peak AF Grid-No.1 Voltage. . . .	18	20	volts
Zero-Signal Plate Current. . . .	52	78	ma
Max.-Signal Plate Current. . . .	58	85	ma
Amplification Factor . . . . .	8	-	
Transconductance . . . . .	5250	-	μmhos
Load Resistance. . . . .	4000	4000	ohms
Total Harmonic Distortion. . . .	6	5.5	%
Max.-Signal Power Output . . . .	1.4	1.8	watts

### Maximum Circuit Values:

Grid-No.1-Circuit Resistance:

For fixed-bias operation . . . . .	0.1 max.	megohm
For cathode-bias operation . . . . .	0.5 max.	megohm

### PUSH-PULL AF POWER AMPLIFIER - Class A<sub>1</sub>

### Maximum Ratings, Design-Center Values:

PLATE VOLTAGE. . . . .	400 max.	volts
GRID-No.2 (SCREEN-GRID) VOLTAGE . . . . .	400 max.	volts
GRID-No.2 INPUT. . . . .	3 max.	watts
PLATE DISSIPATION. . . . .	23 max.	watts
PEAK HEATER-CATHODE VOLTAGE:		
Heater negative with respect to cathode.	200 max.	volts
Heater positive with respect to cathode.	200 max.	volts

### Typical Operation:

*Unless otherwise specified, values are for 2 tubes*

Plate Voltage. . . . .	250	270	volts
Grid-No.2 Voltage. . . . .	250	270	volts
Grid-No.1 (Control-Grid) Voltage.	-16	-17.5	volts
Peak AF Grid-No.1-to-Grid-No.1 Voltage. . . . .	32	35	volts



5881

5881

## BEAM POWER TUBE

Zero-Signal Plate Current. . .	120	134	ma
Max.-Signal Plate Current. . .	140	155	ma
Zero-Signal Grid-No.2 Current.	10	11	ma
Max.-Signal Grid-No.2 Current.	16	17	ma
Plate Resistance (Approx., per tube). . . . .	24500	23500	ohms
Transconductance (Per tube). .	5500	5700	$\mu$ hos
Effective Load Resistance (Plate to plate) . . . . .	5000	5000	ohms
Total Harmonic Distortion. . .	2	2	%
Max.-Signal Power Output . . .	14.5	17.5	watts

**Maximum Circuit Values:**

Grid-No.1-Circuit Resistance:

For fixed-bias operation . . . . .	0.1 max.	megohm
For cathode-bias operation . . . . .	0.5 max.	megohm

**PUSH-PULL AF POWER AMPLIFIER - Class AB<sub>1</sub>****Maximum Ratings, Design-Center Values:**

PLATE VOLTAGE. . . . .	400 max.	volts
GRID-No.2 (SCREEN-GRID) VOLTAGE. . . . .	400 max.	volts
GRID-No.2 INPUT. . . . .	3 max.	watts
PLATE DISSIPATION. . . . .	23 max.	watts
PEAK HEATER-CATHODE VOLTAGE:		
Heater negative with respect to cathode.	200 max.	volts
Heater positive with respect to cathode.	200 max.	volts

**Typical Operation:***Values are for 2 tubes*

Plate Voltage. . . . .	360	360	volts
Grid-No.2 Voltage. . . . .	270	270	volts
Grid-No.1 (Control-Grid) Voltage†	-22.5	-22.5	volts
Peak AF Grid-No.1-to-Grid-No.1 Voltage. . . . .	45	45	volts
Zero-Signal Plate Current. . . . .	88	88	ma
Max.-Signal Plate Current. . . . .	132	140	ma
Zero-Signal Grid-No.2 Current. . .	5	5	ma
Max.-Signal Grid-No.2 Current. . .	15	11	ma
Effective Load Resistance (Plate to plate) . . . . .	6600	3800	ohms
Total Harmonic Distortion. . . . .	2	2	%
Max.-Signal Power Output . . . . .	26.5	18	watts

**Maximum Circuit Values:**

Grid-No.1-Circuit Resistance:†

For fixed-bias operation . . . . .	0.1 max.	megohm
For cathode-bias operation . . . . .	0.5 max.	megohm

†: see next page.



## BEAM POWER TUBE

### PUSH-PULL AF POWER AMPLIFIER - Class AB<sub>1</sub>

Triode Connection - Grid No. 2 Connected to Plate

#### Maximum Ratings, Design-Center Values:

PLATE VOLTAGE . . . . .	400 max.	volts
PLATE DISSIPATION . . . . .	26 max.	watts
PEAK HEATER-CATHODE VOLTAGE:		
Heater negative with respect to cathode . . . . .	200 max.	volts
Heater positive with respect to cathode . . . . .	200 max.	volts

#### Typical Operation:

*Values are for 2 tubes*

Plate Voltage . . . . .	400	volts
Grid-No. 1 (Control-Grid) Voltage† . . . . .	-45	volts
Peak AF Grid-No. 1-to-Grid-No. 1 Voltage. . . . .	90	volts
Zero-Signal Plate Current . . . . .	65	ma
Max.-Signal Plate Current . . . . .	130	ma
Effective Load Resistance		
(Plate to plate). . . . .	4000	ohms
Total Harmonic Distortion . . . . .	4.4	%
Max.-Signal Power Output. . . . .	13.3	watts

#### Maximum Circuit Values:

Grid-No. 1-Circuit Resistance:†		
For fixed-bias operation. . . . .	0.1 max.	megohm
For cathode-bias operation. . . . .	0.5 max.	megohm

### PUSH-PULL AF POWER AMPLIFIER - Class AB<sub>2</sub>

#### Maximum Ratings, Design-Center Values:

PLATE VOLTAGE . . . . .	400 max.	volts
GRID-No. 2 (SCREEN-GRID) VOLTAGE . . . . .	400 max.	volts
GRID-No. 2 INPUT . . . . .	3 max.	watts
PLATE DISSIPATION . . . . .	23 max.	watts
PEAK HEATER-CATHODE VOLTAGE:		
Heater negative with respect to cathode . . . . .	200 max.	volts
Heater positive with respect to cathode . . . . .	200 max.	volts

#### Typical Operation:

*Values are for 2 tubes*

Plate Voltage . . . . .	360	360	volts
Grid-No. 2 Voltage . . . . .	225	270	volts
Grid-No. 1 (Control-Grid) Voltage <sup>■</sup> . . . . .	-18	-22.5	volts
Peak AF Grid-No. 1-to-Grid-No. 1			
Voltage . . . . .	52	72	volts
Zero-Signal Plate Current . . . . .	78	88	ma

† The type of input coupling used should not introduce too much resistance in the grid-No. 1 circuit. Transformer- or impedance-coupling devices are recommended.

■: See next page.



5881

5881

### BEAM POWER TUBE

Max.-Signal Plate Current . . .	142	205	ma
Zero-Signal Grid-No.2 Current .	3.5	5	ma
Max.-Signal Grid-No.2 Current .	11	16	ma
Effective Load Resistance (Plate to plate). . . . .	6000	3800	ohms
Total Harmonic Distortion . . .	2	2	%
Max.-Signal Power Output. . . .	31	47	watts

#### Maximum Circuit Values:

Grid-No.1-Circuit Resistance: <sup>■</sup>

- For fixed-bias operation. . . . . 0.1 max. megohm
- For cathode-bias operation. . . . . Not recommended

<sup>■</sup> Driver stage should be capable of supplying the specified driving power at low distortion to the No.1 grids of the AB<sub>2</sub> stage. To minimize distortion, the effective resistance per grid-No.1 circuit of the AB<sub>2</sub> stage should be held at a low value. For this purpose, the use of transformer coupling is recommended.

Curves shown under Types 6L6, 6L6-G also apply to the 5881

