



T.			$U_f$	$I_f$	$U_{tr}$	$U_o$	$U_p$	$I_o$	$I_p$	$U_{f/k}$	$R_{tr}$	$C_F$
			V	A	V	V	V	mA	mA	V	$\Omega$	$\mu F$
CY 1	eur	1	20	0,2	$\left\{ \begin{array}{l} 127 \\ 170 \\ 170 \\ 250 \\ 250 \end{array} \right.$			75			0	8
CY 1 C	Mul	2	20	0,2				75			0	8
CY 31	eur	3	20	0,2				75			75	32
								75			0	8
								75			350	125
U 201	Maz	3	20	0,2	$\left\{ \begin{array}{l} 110 \\ 230 \end{array} \right.$	110		90		0	32	
						235	750	90	700	550	50	16

Equivalents

C 10 B ER = CY 1 C	TW 1 Dar = CY 1	V 20 Tu = CY 1 C
E 20 U Mul = CY 1	TW 1 P Dar = CY 1	V 20 S Tu = CY 1
G 2080 Tri = CY 1	TW 10 Dar = CY 1 C	V 2018 Tu = CY 1
RE 2020 Vat = CY 1	UE 1 Oxt = CY 1	V 2118 Tu = CY 1 C
RS Fer = CY 1	UEG 51 Sat = CY 1	VEG 51 Sat = CY 1
RZ Fer = CY 1 C	UR 1 Mul = CY 1	13 U 6 Ult = CY 1
TCY 1 Tu = CY 1	UR 1 C Mul = CY 1 C	20 Y 1 TKD = CY 1
TV 1 P Dar = CY 1	UY 1 Dar = CY 1	

