



T.			$U_f$ V	$I_f$ A	$U_a$ V	$U_{g2}$ V	$U_{g1}$ V	$I_a$ mA	$I_{g2}$ mA	S	$R_i$ M $\Omega$
B 2041	Phil	1	20	0,18	100	0	0	2	0	1,1	0,4
B 2042	Phil	2	20	0,18	200	60	-2	4	1,9	1	0,4
B 2046	Phil	3	20	0,18	200	100	-2	3	1,1	2,4	2
B 2052 T	Phil	2	20	0,18	200	100	-2	3	0,2	2	0,45

Equivalents

CT 41	Dar	=	B 2041	H 1818 D	Val	=	B 2052 T	S 25	Tlf	=	B 2041
CT 42	Dar	=	B 2042	H 2018 D	Val	=	B 2042	S 100	Tlf	=	B 2042
CT 46	Dar	=	B 2046	H 2518 D	Val	=	B 2046	S 2010 N	Tlf	=	B 2046
CT 52	Dar	=	B 2052 T	NDG 180	Sat	=	B 2041	S 2018	Tlf	=	B 2052 T
DC. Sup. SC.	Imp	=	B 2052 T	NDG 480	Sat	=	B 2041	S 2030 N	Dar	$\approx$	B 2046
DC. Scr. O.	Imp	=	B 2042	NPG 45	Sat	=	B 2042	S 2035	Val	=	B 2041
DG 20	Mul	=	B 2041	NSS 180	Sat	=	B 2052 T	S 2035 N	Val	=	B 2041
DG 2018	Tu	=	B 2041	NSS 183	Sat	=	B 2046	REN 1817 d	Val	=	B 2041
DSP 1	MOG	$\approx$	B 2046	SG 20	Mul	=	B 2042	REN 2018	Cas	=	B 2052 T
D 2010 N	Tri	=	B 2041	SG 20 A	Mul	=	B 2042	RENS 1817 d	Cas	=	B 2052 T
G 9002	Rec	=	B 2052 T	SG 2018	Vat	=	B 2042	RENS 1818	Cas	=	B 2046
HP 20	Mul	=	B 2046	SG 2118	Vat	=	B 2046	RENS 1820	Ult	=	B 2052 T
HP 2018	Tu	=	B 2046	SP 20	Mul	$\approx$	B 2046	RENS 1884			