





T.	eur amer			U_f		I_f	U_a	U_{g2}	U_{g1}	I_a	I_{g2}	S	R_i	R_k	P_a	P_{g2}
				V	A											
EF 731 5900 ¹⁾	1			6,3	0,15	{ 100 165 }	100	155	-1,2 ÷ -14 maximum	7,2	2,2	4,5 ÷ 0,025 ($I_k = 16,5$ mA)	0,26	120	1,1	0,55
	2			6,3	0,15											

T.	$C_{g1/k}$		$C_{a/k}$		$C_{g1/a}$	
	pF	pF	pF	pF	pF	vide
EF 731	4	4,3	1,9	3,4	0,03	*5
					0,015	*6

Equivalents EF 731

EF 71	eur	5899 ²⁾	int
EF 761 ³⁾	RFT		

1) vide *4, a, b, c ($U_f = 6,3$ V ± 10%)
 2) vide *4, a, b, c, d, e, f, g ($U_f = 6,3$ V ± 5%)
 3) vide *4

