## DIAMETER 6" NOMINAL

## **6EG7**

SKC7

0.415

## Oscilloscope Tube

ELECTROSTATIC FOCUS. ELECTROSTATIC DEFLECTION

Suitable for Assymetrical Deflection


## DATA

GENERAL:

Y Plate

II and an IV 1		
Heater: Voltage .	4.0 .	. a.c. or d.c. volts.
Current	1.0 .	amp.
Direct Inter-electrode C	lapacitances.	-
Modulator to all other	electrodes .	$25\mu\mu f$ .
Each X Plate to all other		$\cdot$ . $25\mu\mu f$ .
Each Y Plate to all other	er electrodes .	$.$ $25\mu\mu f.$
One X to one Y Deflect	or Plate .	$2.5\mu\mu f$ .
Cathode to all other ele	ctrodes	15μμf.
Screen:		• •
Fluorescence		Green.
Persistence		
(10m sec. mi	n /100m	C 10/ 1 1/1 1 1 1 1 1
Focusing Method . Deflecting Method . Overall Length . Greatest Diameter of Bu Minimum Useful Screen Mounting Position		Electrostatic.
Deflecting Method .		Electrostatic.
Overall Length .		421 ± 10 mm.
Greatest Diameter of Bu	nib	163 mm.
Minimum Useful Screen	Diameter	130 mm.
Mounting Position	Diameter .	Any
Base		
	• • • •	. B.12.D.
Die 1 Madulas		
Pin 1—Modulator.	(6) (7)	Pin 8Y2.
Pin 2—Cathode.	(5)	Pin 9—X2.
Pin 3—Heater.	1 K 2 X	Pin 10-Anode 3 and
Pin 4—Heater.		Internal Conductive
Pin 5—Anode 1.		coating.
Pin 6—Anode 2.	(2)	Pin 11—X1.
Pin 7—No connection.	(1) (12)	Pin 12—Y1.
in , its connection.		
Typical Operation Condition		
Typical Operating Condi		
Anode 1 Anode 2	2000 volts.	2000 volts.
Anode 2	800 volts.	530 volte
Anode 3 (6000v. max.)	5000 volts.	3000 volts.
Modulator volts for cut-off		
	-45 to -80 volts.	-45 to -80 volts.
Deflection Sensitivity:	mm/volt.	mm/volt.
X Plate	_ '. <u>-</u> .	0.215
V Plate	0.150	0.213

- Note 2. The angle between the trace produced by X1 and X2 and the trace produced by Y1 and Y2 is  $90^{\circ} \pm 3^{\circ}$ .
- Note 3. The undeflected focused spot will fall within a circle having a 10 mm. radius concentric with the centre of the tube face.



Note 1. When viewing the screen with the tube positioned such that the base spigot is uppermost, a positive voltage applied to the terminal X1 will deflect the spot to the left and a positive voltage applied to the terminal Y1 will deflect the spot upwards.