

Typ	Výrobce	U_f V	I_f A	U_b V	I_a mA	U_1 V	I_1 mA	U_D V	$-U_{g1}$ V	U_{g1} V	S mA/V	μ D^* %*	R_i k Ω	R_a k Ω
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
6977	amer.	1	0,03	50	0,585/ 0,005				0/3					
DM160	Philips	1	0,03	50	0,585/ 0,005				0/3					
1M90	Tesla	1,4	0,025	90 90 67,5 110 170 250	0,25 0,18/— 0,11/— 0,11/— 0,12/— 0,11/—				0/13,5* 0/10 0/7 0/15 0/23 0/34				470 1 000 1 800	
6H5	Raytheon	6,3	0,3	250		250			0/22				1 000	
6N5	Raytheon	6,3	0,15	135		135			0/12				250	
6Z-E1	Toshiba	6,3	0,3	250	5		2/—		0/7					
1M1 1M3	Ediswan Ediswan	1,4	0,025	60 90 110 170 250	0,12 0,25 0,09 0,09 0,09				0/8 0/13,5 0/15 0/23 0/34				560 1 200 2 200	
DM70 DM71	evrop. evrop.	1,4	0,025	60 90 110 170 250	0,12 0,25 0,09 0,09 0,09				0/8 0/13,5 0/15 0/23 0/34				560 1 200 2 200	
1N3	Toyo	1,4	0,025	45—90					10/0					
6AF6-G	Toyo	6,3	0,15	250		140—250	4		160/0				1 000	
6E5D	Toyo	6,3	0,3	250		140—250	3		6,5/0				1 000	
6G-DE2	Toyo	6,3	0,3	250		140—250	3		5/0				1 000	
6G-E12	Toyo	6,3	0,3											
6M-DE1	Toyo	6,3	0,15	200		140—200	3		4,5/0				1 000	
6M-E4	Toyo	6,3	0,22	300		200—300	2		3/0				1 000	
6Z-E11	Toyo	6,3	0,15	130		90—130	2		4,5/0				1 000	
12Z-E6	Toyo	12,6	0,15	250		140—250	3		6,5/0				1 000	
12Z-E8	Toyo	12,6	0,15	130		90—130	2,5		4,5/0				1 000	
12Z-E9	Toyo	12,6	0,15	130		90—130	2,5		4,5/0				1 000	

α β^* °	U_a max V	P_{0 max W	U_1 min max V	$-U_{g1}$ max V	$U_{k/t}$ max V	R_{g1} max M Ω	Poznámka	Typ	Patice
16	17	18	19	20	21	22	23	24	25
10/0*	65			50		1	U_{ba} max = 100 V, I_a max = 750 μ A; *) mm	6977	341
10/0*	65			50		1	I_a max = 750 μ A, *) mm	DM160	
11/0 ^b 11/0 ^b 10/0 ^b 10/0 ^b 10/0 ^b	45—90	0,025				10	*) $l = 0$ mm b) mm I_k max = 300 μ A, U_f max = 1,6 V, U_f min = 0,95 V	1M90	342
90/0								6H5	411
90/0								6N5	
90/9								6Z-E1	
17/0 17/0	90—200	0,025 0,01				10	I_k max = 300 μ A	1M1 1M3	791
17/0 17/0	45—250	0,025 0,01				10	U_{a0} max = 450 V, I_a max = 300 μ A	DM70 DM71	
0/90								1N3	900
0/90								6AF6-G	
0/90								6E5D	
0/90								6G-DE2	
								6G-E12	
0/90								6M-DE1	
0/90								6M-E4	
0/90								6Z-E11	
0/90								12Z-E6	
0/90								12Z-E8	
0/90								12Z-E9	

Skupina 10

