

T.	Image	Image	U _f	I _f	U _o	U _{g2}	U _{k2}	U _{g1}	I _a	I _{g2}	I _{k2}	S	R _j	I _{k1}	P _a	P _{g2}	P _{k2}	U _{f/k1}
EE 1	Phil	1	6,3	0,6	250	150	150	-2,5	8	0,45	-6,5	17	50	10	2	0,1	2	50
EEP 1	Phil	1	6,3	0,6	400	150	200			maximum								
EE 50	eur	2	6,3	0,3	250	250	150	-3	10	0,6	-8	14	250					
EFP 20	eur	3	6,3	0,44	250	250	150	-2	5	0,22	-4	12	500					
EFP 60	Phil	4	6,3	0,37	{ 250 300 }	250	300	-2	20	1,5	-15,6	25	70	8	2	0,4	1	50
TSE 4	Mul	5	4	1,1	250	150	150	-2,5	8	0,7	-6	14,5	100					
4696	Phil	1	6,3	0,6	{ 350 400 }	250	250	-1,7	15,5	1,2	-10,4	19	50	6,3	2,5	0,8	2	150
Z 319	Marc	6	6,3	0,3	250	250	250	-2	26	2,7	-15	29						
6 B 1 II	CCCP	-	6,3	0,4	250	250	150	-2										

EEP1 Fig. 1

U _b	V	R ₁	R _k	U _{g1∞}	U _{o∞}	h
		kΩ	kΩ	mV	V	%
400		85	6,9	34 ÷ 114	10 ÷ 30	1,4 ÷ 4,6
500		105	6	31 ÷ 96	10 ÷ 30	0,9 ÷ 3,2

T.	C _{g1}	C _a	C _{g1/a}	
			pF	pF
EEP 1	10,6	7,5	0,006	
EFP 60	9,2	6	0,004	
Z 319	8	3	0,003	
6 B 1 II	9	4	0,005	









