MINISTRY OF SUPPLY - DLRD RRE

VALVE ELECTRONIC CV 1742

Specification MOS /CV1742	SECURITY			
Issue 1A Dated11.8.59	Specification	<u>Valve</u>		
To be read in conjunction with K1001	UNCLASSIFTED	UNCLASSIFTED		

	-		indica	tes a	ohange
TYPE OF VALVE Ignitron					MARKING
PROTOTYPE - BK. 44					See K1001/4
RATING					BASE
		(a)	(b)	Note	None
Max.Forward Anode Voltage Max Inverse Anode Voltage	(V)	900	2100 2100		See Drawing on Page 3
Max. Anode Current Surge Anode Current (0.15 sec.max.)	(A)	900	600 4500		CONNECTIONS AND DIMENSIONS
Mean Continuous Anode Current Max. Mean Anode Current	(A) (A)	100 150	75 112.5	В	See Drawing on Page 3
Max. Mean Anode Current Max. Outlet Water Temperature Min. Inlet Water Temperature Min. Rate of Flow of Cooling Water (gall/min.)	(20) (20)	200 60 10 1.5	150 45 10 1.5	С	MOUNTING POSITION Vertical only
Auxiliary Anode			L		
Max. Inverse Voltage (Main anode conducting)	(v)		2 5		
Max. Inverse Voltage (Main anode not conducting) Max. Average Current	(V) (A)	1	50 5		
Ignitor Rating Max. Required Positive Voltage Max. Permissible Positive	(v)	3	00	D	
Voltage Max. Permissible Negative Voltage	(v)		5		
Max. Required Current Max. Permissible Current Max. Permissible Average Current	(A) (A) (A)	40 10			
Ignitor Current Averaging-time	(secs)	10)		

NOTES

- A. All limiting values are absolute
- B. Mean for 2 hours averaged over any 2-minute period
- C. Mean for 1 minute averaged over 1 minute
- D. Up to anode voltage

TESTS Page 2.

To be	performed	in	addition	to	those	applicable	in	K1001
-------	-----------	----	----------	----	-------	------------	----	-------

		Test	Test Conditions	Insp. Level	Sym- bol	Limits Min. Max		Units
>	a	Load	Note 1	T.A.		-	-	
	Ъ	Ignitor Resistance	Notes 2 & 5	100%	Rign	20	150	ohms
	ď	Ignitor Operation No. of misfires	Notes 3 & 5	100%		-	0	
	đ	High Voltage	Notes 4 & 5	100%		15	-	kV

NOTES

- Two valves shall be connected in inverse parallel to a 440-volt r.m.s. 50 o/s supply and to a suitable load. A supply of water will be required for . cooling (See rating). The valves shall be operated for 10 minutes on a 50% duty cycle passing a mean anode current of 130 amps in each valve. The duty cycle may be obtained for example by operating 2 c/s on/2 c/s off, but the averaging time must not exceed 8 seconds. Adjustment of the load current by control of ignitor firing is permitted up to a maximum of 30° delay. The valves shall operate satisfactorily.
- The ignitor resistance shall be measured with an ohm-meter having an e.m.f. not exceeding 4 volts.
- 3. The ignitor is fired by discharging a condenser into the ignitor. condenser shall be 4/uF and shall be charged to 500 volts, and discharged through a 0.5 mH inductance and a suitable thyratron. The anode supply shall be such that an arc will be struck and maintained to the anode. Anode voltage shall be greater than 40 volts and the anode current greater than 5 amps when the ignitor fires. The number of misfires shall be recorded by observation of the anode voltage on a cathode ray tube or with a counting device. Each ignitor shall be tested for two minutes. No misfires shall be permitted.
- A 50 c/s AC supply of 15 kV peak voltage shall be applied between anode and cathode through a current limiting resistance and also through a second resistance of suitable value shorted by a neon indicator lamp. Flashing of the indicator lamp shall cease within 20 seconds; if not, the voltage shall be increased to 18-20 kV for 20 mins. after which the test shall be repeated at 15 kV.
- These tests shall be performed with the valve cold.

Page 3

CV1742

