GL-7680

PACKAGED VOLTAGE-TUNABLE MAGNETRON



1000-2300 MEGACYCLES

1 WATT CW OUTPUT

The GL-7680 is a packaged voltagetunable magnetron for voltage-tunable operation in the 1000-to-2300-megacycle frequency range. It is a complete r-f power source package requiring only input power connections and an r-f power output connection and has a minimum CW power output of one watt across the entire frequency range. The tube may be voltage-tuned over a portion or all of the frequency range for which it is designed or operated at a fixed frequency. The voltage-frequency relationship is essentially linear.

Electrical		Mechanical	
Cathode—Directly Heated	Maximum	Mounting Position—Any Net Weight	Pounds
Filament Voltage* 2.3 2.6 Filament Current 3.0	2.8 Volts — Amperes	Thermal	
		Type of Cooling—Forced Air Air Flow	
		Maximum 50	С

MAXIMUM RATINGS-ABSOLUTE VALUES

Anode Voltage	2000 Volts	Injection Electrode Current		
Anode Current	. 20 Milliamperes	Filament Current		Amperes
Power Input, with forced-air cooling	g. 45 Watts	Voltage Standing Wave Ratio	1.5	
Injection Electrode Voltage	500 Volts			

TYPICAL OPERATION


Operation with 60-cycle Sweep Voltage in Wide-Band Circuit		Anode Current, average5 to 15 Injection Electrode Voltage, positive	Milliamperes
Filament Voltage*, approximate. 2.60	Volts	with respect to cathode 200 to 400	Volts
Filament Current3.0		Injection Electrode Current0.1	Milliamperes
Tunable Range†1000-2300	Megacycles	Voltage Standing Wave Ratio of	
Tuning Sensitivity, approximate1.2	Megacycles per Volt	Load1.3	
Anode Voltage at 1.6		Power Output, minimum1.0	Watts
Kilomegacycles1400	Volts	Variation over BandLess than 4:1	

^{*} Filament current should be adjusted to 3.0 amperes.

CAUTION: A clearance of nine inches between ferromagnetic materials and the tube will prevent any serious change of the operating characteristics.



[†] Frequency controlled by anode voltage.



*Note: An external connection is required between the cold cathode lead and one of the heater leads.

